

### S1AW THRU S1MW

### **Surface Mount General Purpose Silicon Rectifiers**

Reverse Voltage - 50 to 1000 V

Forward Current - 1 A

#### **PINNING**

PIN	DESCRIPTION
1	Cathode
2	Anode



#### **Maximum Ratings and Electrical characteristics**

Ratings at 25°C ambient temperature unless otherwise specified. Single phase half-wave 60 Hz, resistive or inductive load, for capacitive load current derate by 20 %.

Parameter	Symbols	S1AW	S1BW	S1DW	S1GW	S1JW	S1KW	S1MW	Units
Maximum Repetitive Peak Reverse Voltage	V <sub>RRM</sub>	50	100	200	400	600	800	1000	٧
Maximum RMS voltage	V <sub>RMS</sub>	35	70	140	280	420	560	700	>
Maximum DC Blocking Voltage	V <sub>DC</sub>	50	100	200	400	600	800	1000	٧
Maximum Average Forward Rectified Current at Ta = 65 °C	I <sub>F(AV)</sub>	1						Α	
Peak Forward Surge Current 8.3 ms Single Half Sine Wave Superimposed on Rated Load (JEDEC Method)	I <sub>FSM</sub>	25						Α	
Maximum Instantaneous Forward Voltage at 1 A	V <sub>F</sub>	1.1						٧	
Maximum DC Reverse Current Ta = 25 °C at Rated DC Blocking Voltage Ta = 125 °C	I <sub>R</sub>	5 50						μА	
Typical Junction Capacitance 1)	Cj	4						pF	
Typical Thermal Resistance <sup>2)</sup>	R <sub>eJA</sub>	180						°C/W	
Operating and Storage Temperature Range	$T_{j},T_{stg}$	-55 ~ <b>+</b> 150						°C	

<sup>1)</sup> Measured at 1 MHz and applied reverse voltage of 4 V D.C

<sup>2)</sup> Thermal resistance from junction to ambient at 0.375" (9.5 mm) lead length, P.C.B. mounted



## S1AW THRU S1MW

Fig.1 Forward Current Derating Curve




Fig.2 Typical Instaneous Reverse Characteristics




Fig.3 Typical Forward Characteristic






Fig.4 Typical Junction Capacitance



# S1AW THRU S1MW


### PACKAGE OUTLINE


Plastic surface mounted package; 2 leads





Ε-





Top View

Bottom View

UNIT		Α	С	D	Е	е	g	H <sub>E</sub>	∠
mm	max	1.1	0.20	2.9	1.9	1.1	0.9	3.8	
	min	0.9	0.12	2.6	1.7	0.8	0.7	3.5	7°
mil	max	43	7.9	114	75	43	35	150	,
	min	35	4.7	102	67	31	28	138	

### The recommended mounting pad size

